



www.idx.tv

Specifications

- DC output : 1 channel (4 pin XLR connector, No.1 minus, No. 4 plus)
- Output Voltage : Voltage of ENDURA batteries
- Discharge current : Maximum 10A
- Number of batteries to be used : Maximum 4 x of E-10 / E-7 (PowerLinked)
- LED display : Output voltage 14V or higher Green LED on
: Output voltage below 14V Red LED on
: Output voltage 12V or below LED off (power off)
- Dimensions : 80(W) x 165(H) x 98(D)mm [128(W)mm feet extended]
- Weight : Approx. 700g

Applicable batteries

All IDX ENDURA Battery (ELITE, E-10, E-10S, E-7, E-7S)

Caution

Maximum discharge current when using 2 x E-7 or E-7S is 9.6A (maximum 4.8A per one ENDURA E-7 or one E-7S). Loads over 8A may activate the battery protection circuit and automatically stop the supply of power.

Maximum discharge current when using 2 x E-10 or E-10S is 13.2A (maximum 6.6A per one ENDURA E-10 or one E-10S). Loads over 13.2A may activate the battery protection circuit and automatically stop the supply of power.

In Japan/Asia

IDX Company, Ltd.
6-28-11 Shukugawara,
Tama-ku, Kawasaki-Shi,
Kanagawa-ken 214-0021,
Japan

Sales and service

Phone +81-44-850-8801
Fax +81-44-850-8838
E-mail idx.japan@idx.tv

In the United States

IDX System Technology, Inc.
1602 Lockness Place,
Torrance, CA 90501
USA

Sales and Service

Phone +1-310-891-2800
Fax +1-310-891-3600
E-mail idx.usa@idx.tv

In Europe/Middle East

IDX Technology Europe Ltd.
Unit 9, Langley Park,
Waterside Drive, Langley,
Berkshire SL3 6EZ,
England

Sales and service

Phone +44-1753-547-692
Fax +44-1753-546-660
E-mail idx.europe@idx.tv