

# SD-1E

## ベルト装着型バッテリーホルダー

仕 様	● DC-OUT	: 1系統出力 (4ピン XLR メス)
	● 出力電圧	: 接続バッテリー電圧 ①－ ④＋ 7.2V ②＋ ③－
	● 最大放電電流	: ① ④ Pin Max.6.5 A ② ③ Pin Max.2A
	● バッテリー取付可能数	: Max. 2個 (パワーリンク時)
	● 外形寸法	: 67.5(W)×106(H)×34.5(D)mm
	● 重 量	: 約 280 g

### 適合バッテリー

ELITE / E-10 / E-10S / E-7 / E-7S 他これに準ずる機構を有するバッテリーパック。

### ご使用上の注意

上記適合バッテリーを装着して電源供給される場合の最大出力電流は、① ④ 側では 6.5A、② ③ 側では 2A です。

ご使用される機器に適正な出力を供給するため、用途にあった DC ケーブルをご使用下さい。また、ご使用される機器の入力電圧をご確認の上、接続して下さい。

お問合せは営業部へ

株式会社アイ・ディー・エクス  
神奈川県川崎市多摩区宿河原 6-28-11  
電話 : 044-850-8801 FAX : 044-850-8838





SD-1E

**ENDURA POWER BELT /  
DV ADAPTOR**

**SPECIFICATIONS**

DC output	:	1 channel	XLR 4 Pin (Female)
Output voltage	:	Battery Voltage	Pin No's : 1 minus / 4 plus
	:	7.2V	Pin No's : 2 plus / 3 minus
Discharge current	:	Pin No,1&4	Maximum 6.5A
	:	Pin No,2&3	Maximum 2A
Number of batteries	:	Maximum 2 (2 in PowerLink mode)	
Dimensions	:	67.5(W) x 106(H) x 34.5(D) mm approx	
	:	2.66(W) x 4.17(H) x 1.36(D) inches approx	
Weight	:	Approx. 280g / Approx. 0.62 lbs.	

**APPLICABLE BATTERIES**

All IDX ENDURA System Li-ion Battery : ELITE / E-10 / E-10S / E-7 / E-7S

**CAUTION**

1. Maximum discharge current when using 7.2V output voltage is 2A.
2. When powering 7.2V equipment be sure to follow XLR wiring instruction  
**i.e. For 7.2V Output Pin No's : 2 = Plus & 3 = Minus**

**In Japan/Asia**

IDX Company, Ltd.  
6-28-11 Shukugawara,  
Tama-ku, Kawasaki-Shi,  
Kanagawa-ken 214-0021,  
Japan

**Sales and service**

Phone +81-44-850-8801  
Fax +81-44-850-8838  
E-mail [idx.japan@idx.tv](mailto:idx.japan@idx.tv)

**In the United States**

IDX System Technology, Inc.  
1602 Lockness Place,  
Torrance, CA 90501  
USA

**Sales and Service**

Phone +1-310-891-2800  
Fax +1-310-891-3600  
E-mail [idx.usa@idx.tv](mailto:idx.usa@idx.tv)

**In Europe/Middle East**

IDX Technology Europe, Ltd.  
Unit 9, Langley Park,  
Waterside Drive, Langley,  
Berkshire SL3 6EZ,  
England

**Sales and service**

Phone +44-1753-547-692  
Fax +44-1753-546-660  
E-mail [idx.europe@idx.tv](mailto:idx.europe@idx.tv)